

1B 05 / 05 0027



INVESTOR IN PEOPLE

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

REC'D 26 JAN 2005

WIPO

PCT

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.

In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

Signed

Dated 12 January 2005

**PRIORITY
DOCUMENT**


SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

Patents Form 1/77

Patents Act 1977

07JAN04 EB63531-2 002879
P01/7700 0.00-0400213.5 NONE

The
Patent
Office



1/77

The Patent Office

Cardiff Road
Newport
Gwent NP10 8QQ

Request for grant of a patent
(See notes on the back of this form. You can also get an explanatory leaflet from the Patent Office to help you fill in this form)

1.	Your reference	PHGB040005GBP		
2.	Patent application number (The Patent Office will fill in this part)	07 JAN 2004	0400213.5	
3.	Full name, address and postcode of the or of each applicant (<u>underline all surnames</u>)	KONINKLIJKE PHILIPS ELECTRONICS N.V. GROENEWOUDSEWEG 1 5621 BA EINDHOVEN THE NETHERLANDS 07419294001		
	Patents ADP Number (<i>if you know it</i>)	07419294001		
	If the applicant is a corporate body, give the country/state of its incorporation	THE NETHERLANDS		
4.	Title of the invention	ELECTROLUMINESCENT DISPLAY DEVICES		
5.	Name of your agent (<i>if you have one</i>)			
	"Address for service" in the United Kingdom to which all correspondence should be sent (<i>including the postcode</i>)	Philips Intellectual Property & Standards Cross Oak Lane Redhill Surrey RH1 5HA		
	Patents ADP number (<i>if you know it</i>)	08359655001 ✓		
6.	If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (<i>if you know it</i>) the or each application number	Country	Priority Application number	Date of filing
7.	If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application	Number of earlier application	Date of filing (day/month/year)	
8.	Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer "Yes" if:	YES		
	a) any applicant named in part 3 is not an inventor, or			
	b) there is an inventor who is not named as an applicant, or			
	c) any named applicant is a corporate body.			
	See note (d))			

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form.
Do not count copies of the same document.

Continuation sheets of this form

Description	11
Claims(s)	4
Abstract	1
Drawings	4 only

10. If you are also filing any of the following, state how many against each item:

Priority Documents

Translations of priority documents

Statement of inventorship and right

to grant of a patent (*Patents Form 7/77*)

Request for preliminary examination and

search (*Patents Form 9/77*)

Request for substantive examination

(*Patents Form 10/77*)

Any other documents

(*Please specify*)

11. I/We request the grant of a patent on the basis of this application.

Signature

Date

6/1/04

12. Name and daytime telephone number of person to contact in the United Kingdom

01293 81 5280

P L WILLIAMSON

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or any such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.*
- Write your answers in capital letters using black ink or you may type them.*
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.*
- If you have answered "Yes" Patents Form 7/77 will need to be filed.*
- Once you have filled in the form you must remember to sign and date it.*
- For details of the fee and ways to pay please contact the Patent Office.*

DESCRIPTION

ELECTROLUMINESCENT DISPLAY DEVICES

5 This invention relates to electroluminescent display devices, particularly active matrix display devices having thin film switching transistors associated with each pixel.

 Matrix display devices employing electroluminescent, light-emitting, display elements are well known. The display elements may comprise organic
10 thin film electroluminescent elements, for example using polymer materials, or else light emitting diodes (LEDs) using traditional III-V semiconductor compounds. Recent developments in organic electroluminescent materials, particularly polymer materials, have demonstrated their ability to be used practically for video display devices. These materials typically comprise one or
15 more layers of a semiconducting conjugated polymer sandwiched between a pair of electrodes, one of which is transparent and the other of which is of a material suitable for injecting holes or electrons into the polymer layer.

 The polymer material can be fabricated using a CVD process, or simply by a spin coating technique using a solution of a soluble conjugated polymer.
20 Ink-jet printing may also be used. Organic electroluminescent materials exhibit diode-like I-V properties, so that they are capable of providing both a display function and a switching function, and can therefore be used in passive type displays. Alternatively, these materials may be used for active matrix display devices, with each pixel comprising a display element and a switching device
25 for controlling the current through the display element.

 Display devices of this type have current-driven display elements, so that a conventional, analogue drive scheme involves supplying a controllable current to the display element. It is known to provide a current source transistor as part of the pixel configuration, with the gate voltage supplied to
30 the current source transistor determining the current through the display element. A storage capacitor holds the gate voltage after the addressing phase.

Figure 1 shows a known pixel circuit for an active matrix addressed electroluminescent display device. The display device comprises a panel having a row and column matrix array of regularly-spaced pixels, denoted by the blocks 1 and comprising electroluminescent display elements 2 together with associated switching means, located at the intersections between crossing sets of row (selection) and column (data) address conductors 4 and 6. Only a few pixels are shown in the Figure for simplicity. In practice there may be several hundred rows and columns of pixels. The pixels 1 are addressed via the sets of row and column address conductors by a peripheral drive circuit comprising a row, scanning, driver circuit 8 and a column, data, driver circuit 9 connected to the ends of the respective sets of conductors.

The electroluminescent display element 2 comprises an organic light emitting diode, represented here as a diode element (LED) and comprising a pair of electrodes between which one or more active layers of organic electroluminescent material is sandwiched. The display elements of the array are carried together with the associated active matrix circuitry on one side of an insulating support. Either the cathodes or the anodes of the display elements are formed of transparent conductive material. The support is of transparent material such as glass and the electrodes of the display elements 2 closest to the substrate may consist of a transparent conductive material such as ITO so that light generated by the electroluminescent layer is transmitted through these electrodes and the support so as to be visible to a viewer at the other side of the support. Typically, the thickness of the organic electroluminescent material layer is between 100 nm and 200nm. Typical examples of suitable organic electroluminescent materials which can be used for the elements 2 are known and described in EP-A-0 717446. Conjugated polymer materials as described in WO96/36959 can also be used.

Figure 2 shows in simplified schematic form a known pixel and drive circuitry arrangement for providing voltage-programmed operation. Each pixel 1 comprises the EL display element 2 and associated driver circuitry. The driver circuitry has an address transistor 16 which is turned on by a row address pulse on the row conductor 4. When the address transistor 16 is

turned on, a voltage on the column conductor 6 can pass to the remainder of the pixel. In particular, the address transistor 16 supplies the column conductor voltage to a current source 20, which comprises a drive transistor 22 and a storage capacitor 24. The column voltage is provided to the gate of the drive transistor 22, and the gate is held at this voltage by the storage capacitor 24 even after the row address pulse has ended. The drive transistor 22 draws a current from the power supply line 26.

The drive transistor 22 in this circuit is implemented as a p-type TFT, for example a low temperature polysilicon TFT, so that the storage capacitor 24 holds the gate-source voltage fixed. This results in a fixed source-drain current through the transistor, which therefore provides the desired current source operation of the pixel.

One problem with voltage-programmed pixels, particularly using polysilicon thin film transistors, is that different transistor characteristics across the substrate (particularly the threshold voltage) give rise to different relationships between the gate voltage and the source-drain current, and artefacts in the displayed image result.

Various techniques have been proposed for compensating for these threshold voltage variations. Some techniques perform in-pixel measurement of the drive transistor threshold voltage, and add this threshold voltage to the pixel drive signal, so that the combined drive voltage takes account of the threshold voltage. A pixel circuit to perform this can use two storage capacitors, one for the threshold voltage and one for the pixel drive voltage. Additional switching transistors are also required to enable the threshold voltage to be measured, for example by discharging a capacitance across the gate-source junction of the drive transistor until it turns off.

This type of threshold compensation pixel circuit has two phases to the address cycle. In the first phase, the threshold voltage is stored on a threshold capacitor. In the second phase, the pixel data voltage is stored on a data capacitor. One problem with the known arrangement is that the column line is used for the threshold voltage measurement operation, and this column line is coupled to the pixel through the address transistor controlled by the row. This

means that the threshold voltage measurement and the supply of pixel data to the pixel must take place within a row address period.

According to the invention, there is provided an active matrix device
5 comprising an array of display pixels, each pixel comprising:

a current driven light emitting display element;

a drive transistor for driving a current through the display element;

first and second capacitors connected in series between the gate and
source or drain of the drive transistor, a data input to the pixel being provided
10 to the junction between the first and second capacitors thereby to charge the
second capacitor to a voltage derived from the pixel data voltage, and a
voltage derived from the drive transistor threshold voltage being stored on the
first capacitor; and

a discharge transistor connected between the junction between the first
15 and second capacitors and a common line for all pixels of the display.

This device uses a common line as a discharge sink/source for the
threshold voltage measurement operation. By avoiding the use of a data line
for this purpose, the pixel can be in a non-addressed state when the threshold
measurement takes place.

20 Each pixel may further comprise an input transistor connected between
an input data line and the junction between the first and second capacitors.

Each pixel is then preferably operable in two modes, a first mode in
which the input transistor is off and the voltage derived from the drive transistor
threshold voltage is stored on the first capacitor, and a second mode in which
25 the input transistor is on and a data input to the pixel charges the second
capacitor to the voltage derived from the pixel data voltage.

This input transistor is the address transistor for the circuit, and is off
during the threshold measurement stage.

The drive transistor may be a p-type transistor and the source of the
30 drive transistor is then connected to a power supply line. The common line
may then be this power supply line, or it may be a separate line.

Each pixel may further comprise a second transistor connected between the gate and drain of the drive transistor. This is used to control the supply of current from the drain. Thus, by turning on the second transistor, the first capacitor can be charged to the gate-source voltage. The second
5 transistor may be controlled by a first gate control line which is shared between a row of pixels.

In one example, the first and second capacitors are connected in series between the gate and source of the drive transistor.

Each pixel may further comprise a third transistor connected between
10 the drive transistor and the display element. This can be used to isolate the display element during the pixel programming stage.

The display element may comprise an electroluminescent display element

The invention also provides a method of driving an active matrix display
15 device comprising an array of current driven light emitting display pixels, each pixel comprising an display element and a drive transistor for driving a current through the display element, the method comprising, for each pixel:

isolating a data line from the pixel, and while the data line is isolated:

driving a current through the drive transistor, and charging a first
20 capacitor to a resulting gate-source voltage;

discharging the first capacitor through a discharge transistor connected between one terminal of the first capacitor and a common line, until the drive transistor turns off, the first capacitor thereby storing a threshold
voltage;

25 coupling a data line to the pixel, and while the data line is coupled:

charging a second capacitor, in series with the first capacitor between the gate and source or drain of the drive transistor, to a data input voltage from the data line; and

using the drive transistor to drive a current through the display element
30 using a gate voltage that is derived from the voltages across the first and second capacitors.

This method uses a common line as a discharge sink/source for the threshold voltage measurement operation. As mentioned above, avoiding the use of a data line for this purpose enables the pixel to be in a non-addressed state when the threshold measurement takes place.

5 The isolating and coupling preferably comprises switching an address transistor connected between the data line and an input to the pixel, and this address transistor for each pixel in a row is switched on simultaneously by a common row address control line.

10 When the data line is isolated from the pixel and the first capacitor is being charged, the data line is preferably used to provide a data input voltage to another pixel associated with the data line. This provides a pipelined addressing sequence.

The invention will now be described by way of example with reference
15 to the accompanying drawings, in which:

Figure 1 shows a known EL display device;

Figure 2 is a schematic diagram of a known pixel circuit for current-addressing the EL display pixel using an input drive voltage;

20 Figure 3 shows a schematic diagram of a known threshold compensation circuit;

Figure 4 shows a schematic diagram of an example of pixel layout for a display device of the invention;

Figure 5 is a timing diagram for operation of the pixel layout of Figure 5;
and

25 Figure 6 is used to show how the circuit of the invention enables pipelining to be carried out.

The same reference numerals are used in different figures for the same components, and description of these components will not be repeated.

30

Figure 3 shows a known threshold compensation pixel arrangement. Each pixel again has an electroluminescent (EL) display element 2 and a drive

transistor T_D in series between a power supply line 26 and a grounded common cathode 28. The drive transistor T_D is for driving a current through the display element 2.

First and second capacitors C_1 and C_2 are connected in series between the gate and source of the drive transistor T_D . A data input to the pixel is provided to the junction 30 between the first and second capacitors and charges the second capacitor C_2 to a pixel data voltage as will be explained below. The first capacitor C_1 is for storing the drive transistor threshold voltage.

An address transistor A_1 is connected between an input data line 6 and the junction 30 between the first and second capacitors. This address transistor times the application of a data voltage to the pixel, for storage on the second capacitor C_2 .

A second, shorting, transistor A_2 is connected between the gate and drain of the drive transistor T_D . This is used to control a flow of current between the power supply line 26 and the first capacitor C_1 when the drive transistor T_D is on.

A third, isolating, transistor A_3 is connected between the drive transistor T_D and the anode of the display element 2. This is used to turn off the display element 2 during the threshold measurement operation of the pixel programming sequence.

The transistors A_1 to A_3 are controlled by respective row conductors which connect to their gates.

The addressing of an array of pixels involves addressing rows of pixels in turn, with a full row of pixels addressed simultaneously, in conventional manner. The data line 6 comprises a column conductor,

The circuit of Figure 3 can be operated in a number of different ways. One basic operation will be described, and the problems associated with the circuit will be explained.

Only the drive transistor T_D is used in constant current mode. All other TFTs A_1 to A_3 in the circuit are used as switches that operate on a short duty cycle.

The circuit operation is to store the threshold voltage of the drive transistor T_D on C_1 , and then store the data voltage on C_2 so that the gate-source voltage of T_D is the data voltage plus the threshold voltage.

During the threshold voltage measurement, the address transistor A_1 is turned on as is the shorting transistor A_2 . The isolation transistor A_3 is initially on, so that current is driven through the display element for a short time, in order to establish a large gate-source voltage on the drive transistor which turns the drive transistor on.

The isolating transistor A_3 is then turned off, and the current sourced by the drive transistor passes from the source to the drain, through the transistor A_2 , the capacitor C_1 and the address transistor A_1 to the data line 6. A suitable voltage is provided on the data line 6 for this operation, for example the same voltage as the power supply line voltage, and this all takes place within the row address period (namely while the address transistor A_1 is turned on).

The flow of charge changes the voltage stored across the capacitor C_1 until the gate-source voltage approaches the threshold voltage. At this time, the drive transistor turns off. With the capacitor C_2 shorted out (because the power supply line voltage is on the data line 6), the capacitor C_1 then stores and holds the threshold voltage.

Subsequently, the shorting transistor A_2 is turned off, and the pixel data is stored on the capacitor C_2 through the address transistor A_1 . The transistor A_3 is turned on for the illumination period.

Variations to this circuit are of course possible, for example to avoid the need for a pulse of light to be output during the threshold measurement operation. However, a problem remains that a significant part of the address cycle is taken up by the threshold measurement.

The invention provides a pipelined addressing sequence, so that there can be some timing overlap between the control signals of adjacent rows.

Figure 4 shows an example of pixel circuit of the invention. The circuit is identical to that shown in Figure 3, but additionally has a discharge transistor A_4 connected between the junction 30 and the power supply line 26. The function of this transistor is to allow the address transistor A_1 to be turned off

during the threshold voltage measurement cycle, so as to free up the column conductor for use in providing pixel data to the pixels in another row.

The operation of the circuit is explained with reference to Figure 5.

At the beginning of the graphs shown in Figure 5, the display is emitting
5 light from the previous address period. At the beginning of the programming phase, the shorting and discharge transistors A_2 , A_4 are turned on. The junction 30 is then lifted to the power rail voltage, and the gate and drain of the drive transistor T_D are connected together. A short pulse of light is emitted while the gate voltage of the drive transistor is stabilised, and then the isolating
10 transistor A_3 is turned off (plot A_3 in Figure 5 goes high). This directs the drive transistor source-drain current to its own gate. In the same way as for the circuit described above, the gate charges up until the drive transistor gate reaches its threshold voltage, and this is stored on the capacitor C_1 .

This charging of the gate has a relatively long time constant. The
15 invention allows this to be carried out with the address transistor turned off (during period 40), so that the time can be "pipelined" with the programming of other rows of pixels with pixel data.

The shorting and discharge transistors A_2 , A_4 are then turned off, so
20 that the gate of the drive transistor can float, with the threshold voltage of the drive transistor stored across the capacitor C_1 . The isolation transistor A_3 can also be turned on at that time, and no current will flow to the display element until the pixel is addressed with the data voltage.

A short address pulse for the address transistor A_1 is needed at a
25 subsequent time, synchronised with the data on the column (the non-hatched part of the data plot in Figure 5). The column is at a lower voltage than the power line voltage, which pulls down the drive transistor gate voltage, storing the pixel data voltage on C_2 . The combined voltage across the source-gate junction is thus the measured threshold voltage added to the pixel drive voltage.

30 It can be seen that the plots for transistors A_2 and A_4 are the same, so that they can be controlled by a shared control line.

This pipelining of the addressing sequence allows more than one row of pixels can be programmed at any one time. Thus, the addressing signals on lines A_2 to A_4 can overlap with the same signals for different rows. The length of the addressing sequence does not then imply long pixel programming times, and the effective line time is only limited by the time required to charge the second capacitor C_2 when the address line A_1 is high. This time period is the same as for a standard active matrix addressing sequence. The other parts of the addressing mean that the overall frame time will only be lengthened slightly by the set-up required for the first few rows of the display. However this set up can easily be done within the frame-blanking period so the time required for the threshold voltage measurement is not a problem.

Pipelined addressing is shown more clearly in the timing diagrams of Figure 6. The control signals for the transistors A_2 to A_4 have been combined into a single plot, but the operation is as described with reference to Figures 4 and 5. The "Data" plot in Figure 6 shows that the data line 6 is used almost continuously to provide data to successive rows.

In the method of Figures 4 and 5, the threshold measurement operation is combined with the display operation, so that the threshold measurement and display is performed for each row of pixels in turn.

It is possible instead to perform all of the threshold measurements for the full display, and then to address.

There are many variations to the specific circuit layout described above which can work in the same way. Differences may be desired to prevent the flash of light during pixel programming. For example, an additional transistor may be provided which gives the drain of the drive transistor a path to ground so that this path can be used to ensure current flow immediately before threshold measurement, instead of using current flow through the display element.

The circuits can be used for currently available LED devices. However, the electroluminescent (EL) display element may comprise an electrophosphorescent organic electroluminescent display element.

The circuit above has been shown implemented with a p-type drive transistor. The invention enables larger area polysilicon arrays to be fabricated because the pixel circuits compensate for the pixel to pixel variations without requiring longer pixel addressing times. These pixel
5 addressing times become a limiting factor when designing large displays. The invention is particularly suitable for displays in which the drive transistor comprises a LTPS transistor.

The invention can be applied to other transistor technologies, such as microcrystalline silicon.

10 Various other modifications will be apparent to those skilled in the art.

CLAIMS

1. An active matrix device comprising an array of display pixels, each pixel comprising:
 - 5 a current driven light emitting display element;
 - a drive transistor for driving a current through the display element;
 - first and second capacitors connected in series between the gate and source or drain of the drive transistor, a data input to the pixel being provided to the junction between the first and second capacitors thereby to charge the
 - 10 second capacitor to a voltage derived from the pixel data voltage, and a voltage derived from the drive transistor threshold voltage being stored on the first capacitor; and
 - a discharge transistor connected between the junction between the first and second capacitors and a common line for all pixels of the display.
- 15 2. A device as claimed in claim 1, wherein the drive transistor comprises a p-type thin film transistor.
3. A device as claimed in claim 1 or 2, wherein the drive transistor
- 20 comprises a polysilicon or microcrystalline silicon transistor.
4. A device as claimed in claim 3, wherein the drive transistor comprises a low temperature polysilicon transistor.
- 25 5. A device as claimed in any preceding claim, wherein each pixel further comprises an input transistor connected between an input data line and the junction between the first and second capacitors.
- 30 6. A device as claimed in any preceding claim, wherein each pixel is operable in two modes, a first mode in which the input transistor is off and the voltage derived from the drive transistor threshold voltage is stored on the first capacitor, and a second mode in which the input transistor is on and a data

input to the pixel charges the second capacitor to the voltage derived from the pixel data voltage.

7. A device as claimed in any preceding claim, wherein the drive transistor
5 is a p-type transistor and the source of the drive transistor is connected to a power supply line.

8. A device as claimed in claim 7, wherein the common line comprises the
10 power supply line.

9. A device as claimed in any preceding claim, wherein each pixel further
comprises a second transistor connected between the gate and drain of the
drive transistor.

10. A device as claimed in claim 9, wherein the second transistor is
15 controlled by a first gate control line which is shared between a row of pixels.

11. A device as claimed in any preceding claim, wherein the first and
second capacitors are connected in series between the gate and source of the
20 drive transistor.

12. A device as claimed in any preceding claim, wherein each pixel further
comprises a third transistor connected between the drive transistor and the
display element.

13. A device as claimed in any preceding claim, wherein the display
25 element comprises an electroluminescent display element.

14. A device as claimed in claim 13, wherein the electroluminescent (EL)
30 display element comprises an electrophosphorescent organic electroluminescent display element.

15. A method of driving an active matrix display device comprising an array of current driven light emitting display pixels, each pixel comprising a display element and a drive transistor for driving a current through the display element, the method comprising, for each pixel:

5 isolating a data line from the pixel, and while the data line is isolated:

driving a current through the drive transistor, and charging a first capacitor to a resulting gate-source voltage;

discharging the first capacitor through a discharge transistor connected between one terminal of the first capacitor and a common line, until
10 the drive transistor turns off, the first capacitor thereby storing a threshold voltage;

coupling a data line to the pixel, and while the data line is coupled:

charging a second capacitor, in series with the first capacitor between the gate and source or drain of the drive transistor, to a data input
15 voltage from the data line; and

using the drive transistor to drive a current through the display element using a gate voltage that is derived from the voltages across the first and second capacitors.

20 16. A method as claimed in claim 15, wherein the isolating and coupling comprises switching an address transistor connected between the data line and an input to the pixel.

17. A method as claimed in claim 16, wherein the address transistor for
25 each pixel in a row is switched on simultaneously by a common row address control line.

18. A method as claimed in claim 17, wherein the address transistors for one row of pixels are turned on substantially immediately after the address
30 transistors for an adjacent row are turned off.

19. A method as claimed in any one of claims 15 to 18, wherein when the data line is isolated from the pixel and the first capacitor is being charged, the data line is used to provide a data input voltage to another pixel associated with the data line.

5

20. A method as claimed in any one of claims 15 to 19, for driving a display device in which each pixel comprises a p-type drive transistor.

21. A method as claimed in any one of claims 15 to 20, for driving a display
10 device in which the drive transistor comprises a polysilicon or microcrystalline silicon transistor.

22. A method as claimed in claim 21, for driving a display device in which
the drive transistor of each pixel comprises a LTPS transistor.

15

ABSTRACT


ELECTROLUMINESCENT DISPLAY DEVICES

5 An active matrix EL display has first and second capacitors connected in series between the gate and source or drain of a pixel drive transistor. A data input to the pixel is provided to the junction between the first and second capacitors thereby to charge the second capacitor to a voltage derived from the pixel data voltage, and a voltage derived from the drive transistor threshold
10 voltage being stored on the first capacitor. A discharge transistor is connected between the junction between the first and second capacitors and a common line for all pixels of the display.

 This device uses a common line as a discharge sink/source for the threshold voltage measurement operation. By avoiding the use of a data line
15 for this purpose, the pixel can be in a non-addressed state when the threshold measurement takes place.


[Fig. 4]

1/4





PRIOR ART

FIG. 1



PRIOR ART

FIG. 2






FIG. 5




FIG. 6

PCT/IB2005/050027

